

## Panasonic NS700 PRI Caller ID Name & Number (Receive) Telquest Tech Support

**NS700 Web Maintenance Console**  
004.42024

Login as INSTALLER

**Port Property - PRI Port**

Main CO Setting Extension Setting Network Configuration **Network Numbering Plan** Supplementary Service

No.	Shelf	Slot	Port	Party Number ring Plan ID Public	Calling Party Number Numbering Plan ID Private	Calling Party Number Type of Number Public	Calling Party Number Type of Number Private	Called Party Number Numbering Plan ID Public	Called Party Number Numbering Plan ID Private
1	ALL	4	1	Private	Unknown	Unknown	Unknown	Unknown	Private

Here's what you can try.

Go to the PRI card under 1.1 and open the Port Property.

Go to the Network Numbering Plan.

For the Numbering Plan ID and Type of Number the default value is **Unknown**.

For the Public values you can try to change this to what the providers signaling is set to.

Page 1 of 1

OK Cancel Apply

**You can also:**

**Run a ISDN/QSIG Protocol Trace and look in the log to try to determine what values the provider is using and then change your card to match.**