

Page 1

Panasonic KX-NS700 TelQuest International 973-808-4588 Voice Mail Pager Notification Set up

Set like this... Telephone Device \blacksquare Device Notification for Unreceived Message Yes Device Device Device No. 1 ▼| Set like this... **Only Urgent Messages ▼**| No Set like this... Dial Number [0-9 * # T X , ;] 912125551212 See below... No. of Retries 5 **‡** Set like this... Busy Delay Time (min) 1 -Set like this... No Answer Delay Time (min) **‡** 1 Set like this... Use Mode Continuously **▼**| Set like this... Schedule If you want to use a Day Sunday Schedule, set it here... Enable Time Frame No. Start At (HH:MM) **‡** : 0 End At (HH:MM) **:** 0

Telquest Tech Support

Dial Number:

Your first digit is usually a 9 to access a CO Line.

In your system, you may need to dial a different digit.

In some cases, you may need to add a COMMA (,) after the 9. This when you have "Slow Dial Tone" from your telco provider.

After the 9 (and COMMA if you needed it) enter the telephone number as you would normally dial it.

You can monitor the KSUs' attempt to send the Notification by connecting your Teset/Butset to the CO Line that the KSU uses to call out on.

This is usually CO Line 1, if it is idle.

Now you can listen to the call processing or not.