

Avaya IP Office Partner Making Calls While in Night Service Telquest Tech Support

This Help Sheet is only needed if you have assigned a **System Password** as shown below.

System Parameters

System Name	Partner Key
System Mode	Key System
Country	United States
Language	English (US)
Receive IP Address Via DHCP Server	<input type="checkbox"/>
IP Address (LAN1)	192 . 168 . 111 . 234
Sub-Net Mask (LAN1)	255 . 255 . 255 . 0
Default Gateway	192 . 168 . 111 . 1
Automatic Daylight Saving Time	<input checked="" type="checkbox"/>
Number Of Lines	5 *
System Password	xxxx
Log All Caller ID Calls for Users	None

The System Password is used for the following:

Activate and Deactivate Night Service from Extension 10

Activate and Deactivate the Emergency Greeting in the Auto Attendant

Allow calls to be made by members of the Night Service Group when in Night Service

Extensions that are assigned to the Night Service Group will ring on lines that appear on their phone.

If a line is not assigned to a phone and a call comes into that line, it will ring on the Intercom Button.

Extensions that are assigned to the Night Service Group are **Restricted** from making outgoing calls unless the System Password is entered prior to making a call. The Emergency List is not restricted.

The procedure to make an outgoing call is:

Leave the handset in the cradle

Press the **HOLD** button

Dial the System Password

Press an outside line button and make your call

Call: NO AUTHCODE will appear when calling out if an incorrect password was entered