

IPO Essential Edition

Door Phone Setup

Telquest Tech Support

Set an Analog Extension to be a Door Phone



Extension (12)

Click here....

Extension			
Id	Extension	Module	Port
1	0	BD1	1
2	202	BD1	2
3	203	BD1	3
4	204	BD1	4
5	205	BD1	5
6	206	BD1	6
7	207	BP1	7
8	208	BP1	8
25	209	BP2	1
26	210	BP2	2
8000	8000	0	0
8001	8001	0	0

Select an Analog Extension

Set it to IVR Port

OK

Cancel

Help

Click OK

Extn

Analogue

Equipment Classification

☐ Quiet Headset

☐ Paging Speaker

☐ Standard Telephone

☐ Door Phone 1

☐ Door Phone 2

☒ IVR Port


☐ FAX Machine





IPO Essential Edition


Door Phone Setup

Telquest Tech Support

Create a New Hunt Group



HuntGroup		
System Name	Name	Extension
	Door Phone	199
	Main	200
	Overflow 1	500
	Night Hunt	551



IPO Essential Edition

Door Phone Setup

Telquest Tech Support

This Tab

Name it...
This is what will appear on the LCD of the phones when the Door Phone rings

Give it an Extension Number
Work backwards from 200

Set to Collective

	Hunt Group	Voicemail	Fallback	Queuing	Call Recording	App. Ice
Name	Door Phone					
Extension	199					
Ring Mode	Collective					
Overflow Mode	Group					
Hold Music Source	No Change					
Agent's Status on No-Answer Applies To	None					

User List

Extension	Name
-----------	------

Edit... Remove

Click on Edit...

IPO Essential Edition

Door Phone Setup

Telquest Tech Support

Add the Extensions that you want to ring when the Door Phone Button is pressed

Collective HuntGroup 199 Door Phone Select Members

Filters

Extn Name Extn Number

Available Users (8/8)

Name	Extn
Extn8001	8001
Extn8000	8000
Extn210	210
Extn209	209
Extn205	205
Extn203	203
Door Phone 1	207
Analog Fax	208

Members (4/4)

Enabled	Name	Extn
<input checked="" type="checkbox"/>	Extn202	202
<input checked="" type="checkbox"/>	Extn204	204
<input checked="" type="checkbox"/>	Extn206	206
<input checked="" type="checkbox"/>	Operator	0

Append

Remove

OK Cancel Help

Click OK...

IPO Essential Edition

Door Phone Setup

Telquest Tech Support

Also, in the new Hunt Group that you created

This Tab... **Turn Voicemail OFF....**

Hunt Group **Voicemail** Fallback Queuing Voice Recording Announcements SIP

Voicemail Code ☐ Voicemail On

Confirm Voicemail Code ☐ Voicemail Help

Voicemail Email ☐ Broadcast

Voicemail Email ☐ UMS Web Services

☒ Off ☐ Copy ☐ Forward ☐ Alert

Click OK...

OK Cancel Help

You are done.

Click Blue Floppy to Save

File Edit View Tools Help

Save Print Find Warning Checkmark

Go press the button on the Door Phone and make sure it works OK..

Click Here...

Select the Analog Extn

Click Here...

Click Here...

The screenshot shows the 'User' settings page. At the top, there's a 'User' tab with a callout 'Click Here...'. Below it, a list of extensions is shown, with 'Extn207' selected and a callout 'Select the Analog Extn'. The 'ShortCodes' tab is active, and the 'Add...' button is highlighted with a callout 'Click Here...'. The 'Phone Manager Options' section is also visible.

User	
Name	Extension
RemoteManager	
NoUser	
Extn201	201
Extn202	202
Extn203	203
Extn204	204
Extn205	205
Extn206	206
Extn207	207

Extinction207: 207

Hunt Group Membership | Announcements | Personal Directory

User | Voicemail | DND | ShortCodes | Source Numbers | Telep

Phone Manager Options

Add... | Remove | Edit...

Do this in the User settings:

Enter ALL this...

The screenshot shows the 'Edit Short Code' form. The fields are: Code (??D), Feature (Dial Extn), Telephone Number (199), Line Group Id (0), and Locale (empty). A callout 'Enter ALL this...' points to the Feature field.

Code: ??D

Feature: Dial Extn

Telephone Number: 199

Line Group Id: 0

Locale:

Force Account Code: ☐

When you are done, it will look like this below:

Code	Telephone Number	Feature	Line Group Id
??D	199	Dial Extn	0