

# Avaya IP Office Essential

## Hunt Group On/Off via Short Codes

### Telquest Tech Support

#### How to switch Hunt Groups in and out of Night Service

##### Example

This short code is a default within the Manager configuration.

N represents the telephone number of the hunt group to be placed into "Night Service" mode.

Example, when **\*20\*201#** is dialed, hunt group 201 will be **placed into "Night Service"** mode.

- Short Code: \*20\*N#
- Telephone Number: N
- Feature: SetHuntGroupNightService

##### Example

Below is a sample of the short code setup.

N represents the telephone number of the hunt group to be taken out of "Night Service" mode and placed into "In Service" mode.

Example, when **\*21\*201#** is dialed, hunt group 201 will be **taken out of "Night Service"** mode.

- Short Code: \*21\*N#
- Telephone Number: N
- Feature: ClearHuntGroupNightService