

## Avaya IP Office Standard Time Profile Over-Ride Telquest Tech Support

You will need to create 2 new Short Codes.

The first one will set the Time Profile to Inactive mode.

The screenshot shows the 'IP Offices' tree view on the left. The 'Short Code (88)' item is highlighted. A context menu is open over it, showing options: New (Ctrl+N), Cut (Ctrl+X), Copy (Ctrl+C), Paste (Ctrl+V), Delete (Ctrl+Del), Validate, Connect To... (Ctrl+T), Show In Groups, and Customize Columns... Two yellow callout boxes point to the menu: '1. Right Click here...' points to the 'Short Code (88)' item, and '2. Click here...' points to the 'New' option in the menu.

Set the 4 fields below like this...

*200*: Set Time Profile to Latched Inactive	
Short Code	
Code	*200*
Feature	Set Time Profile to Latched Inactive
Telephone Number	"Day"
Line Group ID	0
Locale	
Force Account Code	<input type="checkbox"/>
Force Authorization Code	<input type="checkbox"/>

Close up view

Code	*200*
Feature	Set Time Profile to Latched Inactive
Telephone Number	"Day"
Line Group ID	0
Locale	

Time Profile Name with Quotes...

The second one will set the Time Profile to Active mode.

Set the 4 fields below like this...

**\*201\*: Set Time Profile to Latched Active**

Short Code	
Code	*201*
Feature	Set Time Profile to Latched Active
Telephone Number	Day*
Line Group ID	0
Locale	
Force Account Code	<input type="checkbox"/>
Force Authorization Code	<input type="checkbox"/>

1. Click here...

2. Click here...



Incoming Call Route (6)

When Inactive is selected  
this is where the calls will go

21			
Standard   Voice Recording   Destinations			
TimeProfile	Destination		Fallback Extension
▶ Default Value	202 Jim Smith		▼
Day	▼	AA:AA1	▼
*	▼		▼

When Active is selected  
this is where the calls will go

You can also add buttons to set the Time Profile

Mary Smith: 201\*

Web Self-Administration

User

Voicemail

DND

Short Codes

Source Numbers

Telephony

Forwarding

Dial In

Voice Recording

Button Programming

Button ...	Label	Action	Action Data	
1	ICM 201	Appearance	a=	
2		Appearance	b=	
3		Appearance	c=	
4	Park 1	Call Park	600	
5	Voice Ann	Dial Speech	#	
6				
7				
8	Time Profile Inactive	Dial	*200*	
9	Time Profile Active	Dial	*201*	
10				