

## **Panasonic NS700**

### **Get The IP Address Of The KSU via Extension 101**

### **Telquest Tech Support**

This will only work if the System Password has not been changed from 1234 and Extension 101 has been programmed to access the System Programming.

If you cannot obtain the KSU's IP Address using this Help Sheet, then you will need to find an alternate method like a Network Scanner.

Go to Extension 101

Leave the handset in the cradle

Press the **PROG** button (under the LCD)

Dial \* # **1234** (STAR POUND 1234)

If you see some dots on the display and when you press ENTER you hear 3 beeps, then stop. That means that the System Password has been changed and you must find an alternate method or get the correct System Password.

If the System Password is 1234, you will see **Sys-Pgm No?->** in the display of the phone.

Now, dial **191**

You will see **IP Address** in the display of the phone.

Press **ENTER**

You will see **Mode No. ?->** in the display of the phone.

Dial **1**

You will see **1:MPR LAN IP Address** in the display of the phone.

Press **ENTER**

You will now see the IP Address of the KSU in the display.

Press **EXIT** until you get back to the normal **Date and Time** in the display.