

Panasonic NS700 G Capacity

KX-NS700G System Capacity	Without KX-NSF999W AK		With KX-NSF999W AK			
	Pre-Installed KX-NS700G	Max KX-NS700G	KX-NS700G Max	+1 KX-NS720 Max	+2 KX-NS720 Max	+3 KX-NS720 Max
Trunk(ch)	6	102	102	138	174	210
Legacy	6	38 (30+8)	38 (30+8)	74	110	146
	LCOT	6	12	12	24	36
	PRI23	0	23	23	46	69
	IP	0	64	64		
	SIP	0	64	64		
H.323	0	32	32			
Extension(ch) [DXDP]	22 [22]	26 [26]	166 [168]	198 [208]	230 [248]	262 [288]
Legacy [DXDP]	22 [22]	22 [22]	38 [40]	70 [80]	102 [120]	134 [160]
	SLT	4	4	36 (32+4)	68 (64+4)	100 (96+4)
	DPT [DXDP]	18 [18]	18 [18]	34 (32+2) [38]	66 (64+2) [78]	98 (96+2) [118]
	APT	0	0	8	16	24
	IP	4	4	128**		
IP-PT	4	4	128			
	SIP	4	4	128		
	P-SIP*	4	4	128		
	SIP Phone	0	0	128		
	KX-UT series	4	4	128		
CS (pcs)	0	24	24	32	40	48
DPT-CS(2ch)	0	8	8	16	24	32
	DPT-CS(8ch)	0	4	4	8	12
	IP-CS(8ch)	0	16	16	16	16
	New IP-CS(4ch/8ch)	0	32	32	32	32
	SIP-CS	0	16	16	16	16
PS(DECT)	128	128	128			

* KX-HDV series and KX-NTV series

** When IP extensions over 32 are required or KX-NS720, Expansion Capacity AK (KX-NSF991W) is required.